

The Special Magnetizing Power

EX Magnetizing Power



Uses of the special magnetizing power

- **Type of 1504,1506**

magnetizing for micromotor in either inner or outer ways. The magnetized motors' distributions of magnet fields will be in highly uniformity.

- **Type of 1510-20 II, 2510-2510-30II**

Magnetizing for multi-pole of teeny pole distance rare earth, one equipment may match with two yokes or two coils

- **Type of 1520-30 II V**

polar-anisotropic and tropism magnet automatically can be located the right magnetizing position according to the polarizing axis of the magnets.

- **Type of 4030-30 II**

two work-position uses jointly one magnetizer, magnetizing independently with different voltage.

EX I

EX II

EX III

EX IV

Model	EX-1504-10	EX-1506-10	EX-1510-20 II	EX-1520-30 II V	EX-2510-30 II	EX-4030-30 II
Input Power	AC220V 50~60Hz 10A		AC220V 50~60Hz 15A	AC220V 50~60Hz 30A	AC220V 50~60Hz 40A	AC220V 50~60Hz 60A
Max Output Current	10,000	10,000	20,000×2	30,000×2	30,000×2	30,000×2
Charge Voltage	DC50~1500V		DC50~1500V	DC50~1500V	DC50~2500V	DC50~4000V
Repet Precision Of Charge Voltage	+/- 1V+1 digit		+/- 1V+1 digit	+/- 1V+1 digit		
Charge Time	2 sec		4 sec	5 sec	4 sec	12 sec
The capacity of Condenser	400 uF	600 uF	1000 uF	2000 uF	1000 uF	3000 uF

The Capacity Of Changing	none	400/600	none	1000/2000	none	1000/2000/3000
Main Switch	SCR		SCR	SCR		
Compare Function	Have		Have	Have		
Interior Discharge Circuit	Have		Have	Have		
Enclosure Dimensions	450W×850D×565H	450W×1000D×565H	500W×1000D×900H	600W×900D×1350H		1000W×1000D×2000H
Weight	154Kg	150Kg	200Kg	280Kg	320Kg	1200Kg